

## 5.83" 600×448 ePaper Display HAT für Raspberry Pi



|                  |             |
|------------------|-------------|
| Artikel-Nr.:     | RPI-EINK583 |
| Hersteller:      | Waveshare   |
| Herkunftsland:   | China       |
| Zolltarifnummer: | 84733080    |
| Gewicht:         | 0.123 kg    |



### Übersicht

This is an E-Ink display HAT for Raspberry Pi, 5.83inch, 600x448 resolution, with embedded controller, communicating via SPI interface.

Due to the advantages like ultra low power consumption, wide viewing angle, great effect under sunlight, it is an ideal choice for applications such as shelf label, industrial instrument, and so on.

### Eigenschaften

- No backlight, keeps displaying last content for a long time even when power down
- Ultra low power consumption, basically power is only required for refreshing
- Compatible with Raspberry Pi Zero/Zero W/Zero WH/2B/3B/3B+
- SPI interface, for connecting with controller boards like Raspberry Pi/Arduino/Nucleo, etc.
- Comes with development resources and manual (examples for Raspberry Pi/Arduino/STM32)

### Spezifikationen

- Operating voltage: 3.3V
- Interface: SPI
- Outline dimension: 125.40mm × 99.50mm
- Display size: 118.80mm × 88.26mm
- Dot pitch: 0.198 × 0.197
- Resolution: 600 × 448
- Display color: black, white
- Grey level: 2
- Full refresh time: 3.5s
- Refresh power: 26.4mW(typ.)
- Standby power: <0.017mW
- Viewing angle: >170°

| SYMBOL | DESCRIPTION                                             |
|--------|---------------------------------------------------------|
| VCC    | 3.3V                                                    |
| GND    | Ground                                                  |
| DIN    | SPI MOSI pin                                            |
| CLK    | SPI SCK pin                                             |
| CS     | SPI chip selection, low active                          |
| DC     | Data/Command selection (high for data, low for command) |
| RST    | External reset, low active                              |
| BUSY   | Busy status output, low active                          |

## Lieferumfang

- 5.83inch e-Paper
- ePaper Driver HAT
- RPi screws pack (2 pcs.)
- PH2.0 20cm 8Pin

## Dokumentation / Downloads

- [www.waveshare.com/wiki/5.83inch\\_e-Paper\\_HAT](http://www.waveshare.com/wiki/5.83inch_e-Paper_HAT)

## Weitere Bilder:



